

GORAN GENERATOR

KGVP1-315 GENSET Generating Set Powered By **VOLVO PENTA** **STAMFORD**



Image for illustration purposes only

Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz	252KWe / 315KVA	277KWe / 350KVA
1800rpm, 60 Hz	266KWe / 334KVA	295KWe / 369KVA

Genset Specifications

Engine Make & Model	Volvo Penta TAD1341GE
Origin	SWEDEN
Alternator Type	Stamford HCI444E
Control Panel	Deap Sea - 7310
Circuit Breaker Type	3 Pole MCCB
Tropical Cooling System	°55C
Fully Electronic with Volvo Penta EMS2	
Emission Compliant	
CANBUS SAEJ1939 Interface	

Fuel System	%50	%75	%100
1500rpm, 50 Hz	32.58	47.18	61.62
1800rpm, 60Hz	36.04	51.76	68.33

*Prime Power (l/hr)

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.
Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG32-I, IEC34 CSA C-22.2100, AS 1359, BS 1 6861, B En -6-610002:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data


No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Electronic
Bore, mm	131
Stroke, mm	158
Displacement, l	12.78
Compression Ratio	18.1:1
Starting	24V Electric
Alternators, Amps	24V/80A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440
Protection	IP23
Temperature Rise, °C	125
Regulation	%1.0±
No. of Phases	3
No. of Poles	4

Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
3.35	1.13	1.80	3100	405



KGVP1-315 GENSET **VOLVO PENTA** STAMFORD

Generating Set Powered By

Performances

1500rpm

1800rpm

Engine Efficiency %93

Engine Power

Prime Power, KWm(hp) 374(271) 400(294)
Standby Power, KWm(hp) 411(298) 441(324)

Alternator

Prime Power, KWe 252.03 273

Lubrication System

1500rpm

1800rpm

Oil Consumption (l/hr)

Prime Power 0.04 0.05

Oil Sump Capacity, l

30

Oil System Capacity Include Filters, l

36

Cooling System

1500rpm

1800rpm

Heat Radiation from Engine and Alternator, Power KW

10 22
8 22

Heat Rejection to Coolant and Lube Oil at Standby Power, KW

133 148

Radiator Cooling Air Flow, m³/s

4.7 5.6

Coolant Capacity, l

44

Intake & Exhaust System

1500rpm

1800rpm

Air Flow Combustion at Standby Power, m³/min(cfm)

851(24.1) 1024(29)

Heat Rejection Exhaust at Standby Power, KW

203 235

Exhaust Gas Temperature at Standby °C

414 403

Max Allowable Back Pressure in Exhaust Line, Kpa

10 10

Exhaust Gas Flow at Standby Power, m³/min(cfm)

1836(52) 2190(62)

Accessories

Oil Drain Pump Standard Silencer

Stainless Steel Flexible Anti-Vibration Pads

Genuine Oil (Volvo Penta) Fuel Tank Base Frame for 8hrs

Volvo Penta 'Ready Mix'

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load
- Oil pressure, water temperature, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- Engine
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
 - Battery disconnect switch
- Alternator
 - Permanent magnet generator (PMG)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- General
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)

Genuine - Volvo Penta

- Oil filter, full flow (2)
- Oil filter, bypass (1)
- Fuel filter water separator (1)
- Fuel filter (1)
- Air filter (1)
- Fan belt set (1)
- Coolant filter (1)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

GORAN

GENERATOR

✉ gorangenerator@gorangroup.com

🏠 Iraq-Erbil-60M str.

☎ 07504483162 - 07704483162

🌐 www.gorangroup.com